

# Simulation of Proposed Miniaturized Reconfigurable Antenna for Wireless Communication

Pratiksha Gharde<sup>1</sup>\*, Smita Nagtode<sup>2</sup>

<sup>1</sup>M Tech Scholar, Department of Electronics & Telecommunication Engineering, Datta Meghe Institute of Engineering, Technology & Research, Wardha, Maharashtra, India
<sup>2</sup>Professor, Department of Electronics & Telecommunication Engineering, Datta Meghe Institute of Engineering, Technology & Research, Wardha, Maharashtra, India \*Email: pratikshagharde106@gmail.com DOI: http://doi.org/10.5281/zenodo.2619871

#### Abstract

In recent years, there is a huge demand for reconfigurable antenna technique provides large bandwidth and wideband antennas to satisfy the increasing demands for wireless communication application. The frequency reconfiguration patch antennas that has extensively reduced the complexity in structure and thereby the antenna size. As frequency is inversely proportional to dimension of an antenna, the larger the length the smaller is the frequency of operation.

Keywords-Reconfigurable antenna, PIN diodes, frequency reconfiguration, micro strip patch

## INTRODUCTION

In recent years, there is a huge demand for reconfigurable antenna technique provides large bandwidth and wideband antennas to satisfy the increasing demands for wireless communication application [1].

In communication system, it is difficult to provide a single antenna for different applications. Reconfigurable antenna is an antenna capable of modifying dynamically its frequency and radiation properties in a controlled manner [2]. Reconfigurability can be achieved by using RF PIN diodes, Varactor diode. Reconfigurable antennas can address complex system requirements by modifying their geometry and electrical behaviour, thereby adapting to changes in conditions environmental or system requirements (i.e. enhanced bandwidth, changes in operating frequency, polarization, and radiation pattern) [3].

This work deals with the design of concept of a miniaturized reconfigurable antenna, the most commonly used Micro-Strip Patch antennas are rectangular and circular patch antennas. These patch antennas provided different characteristics such as dual characteristics, circular polarizations, dual frequency operation, frequency agility, broadband width, feed line flexibility, beam scanning [4].

The proposed antenna operates in distinct wireless communication band between the frequency range (1.6 GHz to 5.8 GHz) [5]. Objectives of this work is to calculate overall performance of the reconfigurable and to implement antenna several functionalities on same antenna which is low profile and compact that could be easily integrated to movable devices [6]. To design a Multiband antenna by using switching configuration in reconfigurable antenna. As PIN diodes are used for switching purpose because they require lower biasing voltages. PIN diode operates in two modes the "ON" state, where the diode is forward biased and "OFF" state where the diode is not biased [7].

# ANTENNA GEOMETRY

The antenna design (reference antenna for 2.5 GHz) is implemented in CST microwave studio 2014 and the structure is shown in fig. 1. Substrate material FR-4 (lossy) is used between ground and patch



with dielectric constant of 4.3. Patch has the dimension of 36.85 mm X 44.29 mm and it is fed with quarter wave transformer. On the patch slots are made as shown in fig. 2. To implement frequency reconfigurability a PIN diode (BAP50\_02) is used as a switch. To design the antenna following formulae [8-10]

## Antenna design

- (1) Ground plane
- (2) Substrate
- FR4 (Er=4.4)
- Roger\_RT Duroid(Er=2.32)
- Quartz (Er = 3.8)
- Alumina (Er =10)
- (3) Patch
- Microstrip patch
- Microstrip slot patch
- Printed dipole patch
- (4) Feed
- Microstrip line feed
- Coax feed
- Aperture feed
- Proximity feed

The antenna design is implemented in CST microwave studio 2014. The microstrip antenna consists of a very thin (t) metallic strip (patch) placed on a small fraction of a wavelength (h) above aground plane. The ground plane and a patch are separated by a dielectric with constant [11].

Substrate is used between ground and patch with dielectric constant. Patch is

feed with the microstrip feed line. To implement frequency reconfigurability a PIN diode is used as a switch. To design the antenna following formulae were used: To find the width of the patch,

$$W = \frac{c}{2fr} \sqrt{\frac{2}{\epsilon r + 1}} \tag{1}$$

Where,

 $c = 3 \times 10^8$  m/s,  $f_r$  =Resonating frequency and  $c_r = distantial constant$ 

Er = dielectric constant.

Length of patch can be obtained by  $L=L_{aff}-2\Delta L$ 

$$L = L_{eff} - 2\Delta L \tag{2}$$
  
Where,

$$\Delta L = 0.412h \left[ \frac{(\varepsilon reff + 0.3) \left( \frac{W}{h} + 0.264 \right)}{(\varepsilon reff - 0.258) \left( \frac{W}{h} + 0.8 \right)} \right]$$
(3)

$$\mathcal{E}_{reff=\left(\frac{\varepsilon r+1}{2}\right)+\left(\frac{\varepsilon r-1}{2}\right)\left[1+12\left(\frac{h}{W}\right)\right]^{-1/2}}$$
(4)

$$\text{Leff} = \frac{c}{2fr} \sqrt{\frac{2}{\epsilon reff}}$$
(5)

The dimensions of substrate is given by

$$L_{g=L+6h}$$

$$W_{g=W+6h}$$

$$h = \frac{0.606\lambda}{\sqrt{\varepsilon r}}$$

Feed line length is given by Feedlength $(L_f) = \frac{\lambda_g}{4}$  (6) Guided Wavelength  $\lambda_{g=\frac{\lambda}{\sqrt{\epsilon reff}}}$  (7)

Efficiency of antenna ( $\eta$ )  $\eta = \frac{gain}{directivity} \times 100\%$ 



Figure 1: Microstrip Patch Antenna (reference antenna)





Figure 2: Slotted Microstrip Patch Antenna



Figure 3: The proposed antenna geometry



The dimensions of various parameters used for designing antennas are provided in Table 1.

Table 1: Different parameters value used for designing the reference antenna,	slot antenna
and proposed reconfigurable microstrip patch antenna	

Name /	Value	Description	Туре		^
d_gap	2	diode gap	None		
h	1.6	substrate height	None		
L1	30.0129	diatance from subs	None		
L2	2.2	gap between strip	None		
L3	2.2	width of slot line	None		
Ľ	14.9985	feed length	None		
Lg	88.5976	Substrate length	None	•	
Lр	28.56	patch length	None		
Lt	15.1144	transmission line le	None		
t	0.035	copper thickness	None		
Wf	3.1144	feed width	None		
Wg	73.7154	substrate width	None		v

#### **RESULTS AND DISCUSSIONS**

Graph of return loss versus frequency for microstrip antenna (reference antenna) is shown in fig. 1. Microstrip antenna is radiating at 2.4808 GHz with a return loss of -20.72 dB. Fig.4



Figure 4: Graph of Return Loss Vs frequency for reference Antenna



## Effect of Slots

Slots are made on to the patch as shown in fig. 2. The designed slotted antenna is

radiating between 2.746 GHz to 5.9416 GHz as shown in fig. 5.



Figure 5: Graph of Return loss Vs frequency for Slotted antenna



Figure 6: Polar Diagram



Figure 7: Farfield



## Effect of PIN Diode

PIN Diode is inserted as shown in the fig. 3. For ON condition, the antenna is resonating at six different frequencies with wide bandwidth. For OFF condition, antenna operation is almost same as that of slotted antenna without a PIN Diode but with low return loss and improved bandwidth. When PIN diode is ON, length of the current path increases as compared to the OFF condition. Due to this antenna resonates at lower frequencies for ON condition and high frequencies for OFF condition. The return loss graphs for ON condition and OFF condition are shown



Figure 9: Polar diagram



Figure 10: Farfield



# CONCLUSION

The frequency reconfigurable antenna has been designed and simulated by computer simulation technology (CST) software. The simulation results show that by using PIN diode the antenna can be reconfigured for different frequencies such as 3.3528GHz, 4.0671GHz, 4.6818GHz, 5. 6039GHz.As a result, the proposed antenna is used for various multi frequency systems.

#### ACKNOWLEDGMENT

The authors would like to thanks Dr...P. H. Patil for guidance of paper writing.

## REFERENCES

- R. Soloni, H. S. Rajappa and D. N. Dr. Chandrappa, "Design and Analysis of Multiband Reconfigurable Microstrip Patch Antenna with Switchable Element," IEEE, pp. 288-293, 2017.
- M. Rahim, M. Hamid, N. Samsuri, N. Murad, M. Yusoff and H. Majid, "Frequency Reconfigurable Antenna for Future Wireless Communication System," in the 46th European Microwave Conference, London, UK, 4-6 Oct 2016.
- S. L. Antony, S. Sebastian, S. Joseph, T. John and M. Joy, "Design of Reconfigurable Antenna for Wireless Applications," International Journal of Engineering Research & Technology (IJERT) ISSN: 2278-0181, vol. Vol. 5, no. 5 Issue 03, pp. 809-812, March-2016.
- 4. B. l. Sharma, G. Parmar and M. Kumar, "Design of Frequency Reconfigurable Microstip Patch Antenna for S- band and C- band Applications," IEEE., Vols. 978-1-4673-7231-2/15, 2015.
- 5. P. Chakrapani and S. Raghavan, "Reconfigurable Antenna for Wireless Communication Bands," in" IEEE SPONSORED 2'ND INTERNATIONAL CONFERENCE

ON ELECTRONICS AND COMMUNICATION SYSTEMS, Tiruchirappalli, India, 2015.

- C. Wang, Y. Xing, L. Han and W. Zhang, "Miniaturized frequency Reconfigurable Slot Antenna," IEEE, no. 2, p. 3, 2015.
- 7. R. J. Chitra and N. V., "Frequency Reconfigurable Antenna Using PIN Diodes," IEEE, no. 8, p. 4, 2014.
- M. Fallahpour, M. T. Ghasr and R. Zoughi, "Miniaturized Reconfigurable Multiband Antenna For Multiradio Wireless Communication," IEEE TRANSACTIONS ON ANTENNAS AND PROPAGATION, vol. 62, no. 12, 2014.
- 9. C. G. Christodoulou, Y. Tawk,, S. A. Lane and S. R. Erwin, "Reconfigurable Antennas for Wireless and Space Applications," IEEE, vol. 100, no. 7, 2012.
- 10. I.ROUISSI, F. J.M and H. TRABELSI, "Design of Frequency Reconfigurable Multiband Meander Antenna Using Varactor Diode for Wireless Communication," International Journal of Advanced Computer Science and Applications, vol. 8, no. 3, 2017.
- 11. A. M, R. G and P. S, "A Survey of Different Reconfigurable Antennas for Various Wireless Applications," International Journal of Innovative Research in Computer and Communication Engineering (An ISO 3297: 2007 Certified Organization), vol. 4, no. 2, 2016.

#### **Cite this Article as:**

Pratiksha Gharde, & Smita Nagtode. (2019). Simulation of Proposed Miniaturized Reconfigurable Antenna for Wireless Communication. Journal of Analog and Digital Devices, 4(1), 1–7. http://doi.org/10.5281/zenodo.2619871